

## General Description

Newport Digital's memory for the HP C3000 / C3600 Class systems consists of a single 278-pin ECC memory card. The cards can be configured with 256, 512, 1024 megabytes synchronous dynamic rams (SDRAMs). The C3000 / C3600 systems can be configured with 8 cards.

## System Compatibility

The memory is fully compatible with the HP 9000 Models C3000 and C3600.

## Maximum System Memory

The maximum system memory for the C3000 and C3600 is 8 GB. If HP-UX 10.xx is the OS, then the maximum system memory is 4 GB with only 3.75 GB (3840 MB) of addressable memory.

## Installation Procedure

The installation procedure is quick and easy. Power the system down. Remove the slide panel. Pull the power supply out. Add the memory card to the next DIMM slot using the sequence list. Rotate the power supply back into the system. Replace the slide panel. Power the system up. Verify that the system has the expected RAM size.

## Operating Limits

Operating Temperature: 0-70 degrees Centigrade  
Operating Humidity: 0-95 percent with no condensation

## HP Documentation

HP Visualize B1000/C3000 Owner's Guide (A4985-90013)  
HP Visualize B1000/C3000 UNIX Workstations - Memory DIMMs Removal/Replacement Instructions (A4985-90027)  
HP Visualize B1000/C3000 UNIX Workstations - System Board Removal/Replacement Instructions (A4985-90011)

## Product Warranty

The memory has an unconditional lifetime warranty.

## Ordering Information

<u>Product Description</u>	<u>HP Equivalent</u>	<u>Newport Digital Part Number</u>
HP C3000/C3600 Memory – 256MB	A4994A	11-26-0256
HP C3000/C3600 Memory – 512MB	A4995A	11-26-0512
HP C3000/C3600 Memory – 1GB	NA	11-26-1024

## Newport Digital