

## General Description

Newport Digital's memory card for the HP 9000 Models 340 is configured with 4 megabytes of 80 nanosecond dynamic rams.

## System Compatibility

The memory is fully compatible with the HP 9000 Model 340 workstation.

## Maximum System Memory

The maximum system memory for the HP 9000 Model 340 is 16 megabytes.

## Installation Procedure

The installation procedure is quick and easy. Power the system down. Remove the six screws on the back of the computer. Slide the HP 340 board out of the chassis. Install the memory card in the next 96-pin memory bus connector on the front of the HP 340 CPU board. Slide the CPU board back into the system. Power the system up. Verify that the system has the expected RAM size.

## Power Requirements

4 Megabytes                      0.4 Amps Max (2.00 Watts)                      0.3 Amps Typical (1.50 Watts)

## Cycle and Access Times

The memory cycle and access times are identical to those of the HP 98268A cards.

## Operating Limits

Operating Temperature:                      0-70 degrees Centigrade  
Operating Humidity:                      0-95 percent with no condensation

## HP Documentation

HP 9000 Model 340 Owner's Guide.

## Product Warranty

The memory has an unconditional lifetime warranty.

## Ordering Information

<u>Product Description</u>	<u>HP Equivalent</u>	<u>Newport Digital Part Number</u>
HP 340 Memory – 4 MB	98268AB	11-05-0004

## Newport Digital